
SquareLED Hi-Precision 500W LED 15°-30°

RGBAL DMX512 Channel Table

		Value	Function	
Reduced	Standard			
	1		<u>Hue</u>	
		0-255	HUE 0 to 100%	
	2		<u>H_fine</u>	
		0-255	Hue_fine	
	3		<u>Saturation:</u>	
		0-255	Focus adjustment	
	4		<u>Dimmer intensity :</u>	
		0-255	0-255	

	5		<u>CCT:</u>	
		0-255	0-255	
	6		<u>Ctrl_onff :</u>	
		0-1	HSIC MODE	
		1-255	Monochromatic MODE	
	7		<u>Red Color:</u>	
		0-255	Red 0 to 100%	
	8		<u>Green Color:</u>	
		0-255	Green 0 to 100%	
	9		<u>Blue Color:</u>	
		0-255	<u>Blue</u> 0 to 100%	
	10		<u>Amber Color:</u>	
		0-255	Amber 0 to 100%	
	11		<u>Lime Color:</u>	
		0-255	Lime 0 to 100%	
	12		<u>Strobe:</u>	
		0-5	0Hz	
		5-255	1-20Hz	
	13		<u>Dimmer mode:</u>	
			0-255	
			<u>Dimmer Curve:</u>	
		000-005	None Function	
		006-064	Linear Dimmer Curve	
		065-128	Square Dimmer Curve	

		129-192	I-Square Dimmer Curve	
		193-255	S-Shape Dimmer Curve	
	14	0-255	255, More than 3 seconds	System Reset
	15		<u>Fan Control:</u>	
		0-127	Temperature control mode	
		128-191		Manual
		192-255	High speed mode	
	16		<u>Set Freq:</u>	
		0-80	500Hz	
		81-160	2000Hz	
		161-240	8000Hz	
		240-255	17600Hz	